

## 3 Pole 35A or AC5KV Connector with locking feature 3極コネクタ、ロック付

AC5kV

### Specification

Current rating: 35A at 25°C  
Contact Resistance: 3mΩ max  
Temperature range: -10°C ~ +125°C

### Material

Insulator: PBT, glass filled, Black  
Plug pin: Brass, Phosphor bronze, Gold plating over Ni  
Socket pin  
Louver: Beryllium Copper, Heat treated  
Gold Plated over Ni plating  
Sleeve, Futa: Brass, Gold Plating over Ni plating

<p>プラグインシュレタ Plug Insulator</p> <p><b>M-50P-3-MD</b></p>	<p>ソケットインシュレタ Socket Insulator</p> <p><b>M-50R-3-MD</b></p>								
<p>Plug Pin</p> <table border="1"> <thead> <tr> <th>Part number</th> <th>Wire</th> </tr> </thead> <tbody> <tr> <td><b>UJCP-F40CRMP-L315B</b></td> <td>AWG#10, 5.5mm<sup>2</sup></td> </tr> </tbody> </table>	Part number	Wire	<b>UJCP-F40CRMP-L315B</b>	AWG#10, 5.5mm <sup>2</sup>	<p>Socket Pin</p> <table border="1"> <thead> <tr> <th>Part number</th> <th>Wire</th> </tr> </thead> <tbody> <tr> <td><b>UJCS-F40CRMP-L315B</b></td> <td>AWG#10, 5.5mm<sup>2</sup></td> </tr> </tbody> </table>	Part number	Wire	<b>UJCS-F40CRMP-L315B</b>	AWG#10, 5.5mm <sup>2</sup>
Part number	Wire								
<b>UJCP-F40CRMP-L315B</b>	AWG#10, 5.5mm <sup>2</sup>								
Part number	Wire								
<b>UJCS-F40CRMP-L315B</b>	AWG#10, 5.5mm <sup>2</sup>								
<p>How to order (example)</p> <table> <tbody> <tr> <td><b>M-50P-3-MD</b></td> <td>100pcs</td> </tr> <tr> <td><b>UJCP-F40CRMP-L315B</b></td> <td>300pcs</td> </tr> <tr> <td><b>M-50R-3MD</b></td> <td>100pcs</td> </tr> <tr> <td><b>UJCS-F40CRMP-L315B</b></td> <td>300pcs</td> </tr> </tbody> </table> <p>ハ° 初取り付け寸法図 Mounting dimension</p> <p>公差: ±0.2 Tolerance: ±0.2</p> <p>ハ° 初板厚: t=2.0<sup>+0.4</sup><sub>-0</sub> Panel: t=2.0<sup>+0.4</sup><sub>-0</sub></p> <p>ハ° 初にワンタッチ押し込み装着できます Mounting in one-touch to panel.</p>		<b>M-50P-3-MD</b>	100pcs	<b>UJCP-F40CRMP-L315B</b>	300pcs	<b>M-50R-3MD</b>	100pcs	<b>UJCS-F40CRMP-L315B</b>	300pcs
<b>M-50P-3-MD</b>	100pcs								
<b>UJCP-F40CRMP-L315B</b>	300pcs								
<b>M-50R-3MD</b>	100pcs								
<b>UJCS-F40CRMP-L315B</b>	300pcs								

○ピンと電線の結線に圧着工具が必要です。  
Crimping Tool is needed.

○ピン (ソケット、プラグ 共通) 組込み後、ピン抜き治具を使用するとピンを引き抜けます。  
Both pins (socket and plug) are removal with pin removal tool.

○工具、治具は専用ですのでお問い合わせください。  
Please contact us about tools.